



The **RMI-CC Wall Mounted 3-input Remote Control** is a wall mountable unit intended for installation in areas where control of up to three inputs (and an additional, local stereo to mono line input) may be useful.

The RMI-CC provides three microphone inputs, and two line inputs (resistively mixed to mono). There are three level controls corresponding to the mic and line inputs, an illuminated on/off button, and an illuminated assignable momentary switch (Auto/Manual).

The front cover of the unit is a hinged door with latch. The door swings 180 degrees.

The back of the RMI-CC features dual RJ-45 EtherNet style connectors, either of which may be used to connect the unit to the mixer via Cat5e or better cable.

The RMI-CC is a SmartContol™ designed for use with Ivие Technologies iFlex™ LDS mixers.

Note: Cat5e or better cable must be used to connect the RMI-CC to the iFlex mixer.